



PC Board $\Phi 1.3$

Crimp Terminal

$\Phi 1.3$ Series

FEATURES & BENEFITS:

- Stand-Alone, Board-In
- Secures wire to PC board before wave soldering
- Rapid and economical means of hand wiring PC board
- Wire solders directly to PC board
- No additional contact resistance
- Low profile
- Recommended PC board hole diameter
 $\Phi 1.3 + 0.1/-0$ for 1.60 ± 0.1 mm thick PC board

SPECIFICATION:


Physical:

- Contact: Brass or Phosphor Bronze
- Plating: Pre. Tin over Copper
Post Tin over Copper

REFERENCE INFORMATION:

- Package: Reel
- Designed in : mm


ORDERING INFORMATION AND DIMENSIONS:



A-A SECTION



B-B SECTION



C-C SECTION



Part No.	Material	Plated	PCB Hole	PCB Thickness	Wire Range
T6613-12	Brass	Post-Tin	$\Phi 1.3$	1.6	#22~28
T6613-32	Brass	Pre-Tin			
T6613-52	Phosphor Bronze	Post-Tin			
T6613-72	Phosphor Bronze	Pre-Tin			